



Sommario

4 STEP-DIRECTION outputs



The electrical features are given in section [Electrical features](#).
The connection examples are provided in section [Connection examples](#)

CN13	Terminal	Symbol	Description	Address	
	1A	-	n.c.		
	2A	DIR1+	Output DIRECTION 1	3.PULSE01	
	3A	STEP1+	Output STEP 1		
	4A	DIR2+	Output DIRECTION 2		
	5A	STEP2+	Output STEP 2	3.PULSE02	
	6A	0V	Stepper outputs common		
	1B	-	n.c.		
	2B	DIR1-	Complementary output DIRECTION 1	Complementary output for use in drive with Line-Driver inputs	
	3B	STEP1-	Complementary output STEP 1		
	4B	DIR2-	Complementary output DIRECTION 2		
	5B	STEP2-	Complementary output STEP 2		
	6B	0V	Stepper outputs common		
CN14	Terminal	Symbol	Description	Address	
	1A	-	n.c.		
	2A	DIR3+	Output DIRECTION 3	3.PULSE03	
	3A	STEP3+	Output STEP 3		
	4A	DIR4+	Output DIRECTION 4		
	5A	STEP4+	Output STEP 4	3.PULSE04	
	6A	0V	Stepper outputs common		
	1B	-	n.c.		
	2B	DIR3-	Complementary output DIRECTION 3	Complementary output for use in drive with Line-Driver inputs	
	3B	STEP3-	Complementary output STEP 3		
	4B	DIR4-	Complementary output DIRECTION 4		
	5B	STEP4-	Complementary output STEP 4		
	6B	0V	Stepper outputs common		

Documento generato automaticamente da **Qem Wiki** - <https://wiki.qem.it/>

Il contenuto wiki è costantemente aggiornato dal team di sviluppo, è quindi possibile che la versione online contenga informazioni più recenti di questo documento.