

Sommario



The electrical characteristics are given in paragraph [Electrical features](#).
The wiring examples are given in paragraph [Connection examples](#)

@cnaa@	Terminal	Symbol	Description	Address
	1A		Uscita +24V dc ¹⁾	
	2A	PHA1	Phase A	Count 1 PNP Push-Pull ²⁾
	3A	PHB1	Phase B	
	4A	Z1	Z	2.INP17
	5A	0V	Common for count inputs	2.INP18
	6A	0V		2.CNT01
	7A	0V		1.INT01
	1B		+24Vdc out ³⁾	
	2B	PHA1+	+ PHA	Count 1 Line Driver
	3B	PHB1+	+ PHB	
	4B	Z1+	+ Z	1.INT01
	5B	PHA1-	- PHA	
	6B	PHB1-	- PHB	
	7B	Z1-	- Z	

^{1), 3)} Used to power the encoder. See [Connection examples](#).

²⁾ **PNP/Push-Pull type count input configuration:**

Terminal 5B: connect to terminal 5A

Terminal 6B: connect to terminal 6A

Terminal 7B: connect to terminal 7A

@cnna@	Terminal	Symbol	Description	Address
	1A		Uscita +24V dc ¹⁾	
	2A	PHA2	Phase A	Count 2 PNP Push-Pull ²⁾
	3A	PHB2	Phase B	
	4A	Z2	Z	2.INP19
	5A	0V	Common for count inputs	2.INP20
	6A	0V		2.CNT02
	7A	0V		1.INT02
	1B		+24Vdc out ³⁾	
	2B	PHA2+	+ PHA	Count 2 Line Driver
	3B	PHB2+	+ PHB	
	4B	Z2+	+ Z	1.INT02
	5B	PHA2-	- PHA	
	6B	PHB2-	- PHB	
	7B	Z2-	- Z	

^{1), 3)} Used to power the encoder. See [Connection examples](#).

²⁾ **PNP/Push-Pull type count input configuration:**

Terminal 5B: connect to terminal 5A

Terminal 6B: connect to terminal 6A

Terminal 7B: connect to terminal 7A

Documento generato automaticamente da **Qem Wiki** - <https://wiki.qem.it/>

Il contenuto wiki è costantemente aggiornato dal team di sviluppo, è quindi possibile che la versione online contenga informazioni più recenti di questo documento.