

## Sommario

<b>AN028 - Firmware upgrade procedure with USB on MQ5CF</b> .....	3
<b>Introduction</b> .....	4
<b>Procedure</b> .....	4
<b>Note</b> .....	8



## AN028 - Firmware upgrade procedure with USB on MQ5CF

			
<b>Document:</b>	<b>AN028</b>		
<b>Description:</b>	Firmware upgrade procedure with USB on MQ5CF		
<b>Editor:</b>	Davide Mocellin		
<b>Approver</b>	Giuliano Tognon		
<b>Link:</b>	<a href="http://www.qem.eu/doku/doku.php/appnote/an028">http://www.qem.eu/doku/doku.php/appnote/an028</a>		
<b>Language:</b>	English		
<b>Document Release</b>	<b>Description</b>	<b>Note</b>	<b>Date</b>
01	New manual		09/10/2015

## Introduction

This procedure allows the firmware update, Via the USB port on the back of the MQ5CF controller.




**ATTENTION: The firmware upgrade operation is particularly dangerous if it does not run properly, because it could make damage to the instrument.**

==== Premise =====.


Copy in the root (main folder) of the USB of upgrading, the **FIRMWARE.a21** file.

## Procedure

1. Turn off the instrument.
2. Insert the USB key on the back of the MQ5CF.



3. Turn on the MQ5CF by holding down the **FUNC** button  on the back of the instrument.
4. After a few moments the MQ5CF enters the system functions area. Press the **F1** key  to get to the function **15 - Firmware upgrade**.



5. To execute the function press and hold for 2 seconds the **F7**  button or the **BOOT** button  on the back.
6. A screen is shown for entering the password. The default value is **123**.


Confirm with the **Enter**  button




7. It scans the contents of the USB and shows the name of the firmware file found.

To confirm press the **F7** key  or the **BOOT** key .


To quit the procedure, press the **F1** key  or the **FUNC** key .




8. Start the upgrade process.



9. When you have finished, The following screen is showed for 5 seconds and then the MQ5CF automatically restarts.



10. A report screen appears when you start the MQ5CF that shows the name of the old firmware and the new one. Press the **F1** key  or the **FUNC** key  to proceed with the power on.



The new application is loaded and the procedure is completed.

## Note

The firmware update can be done alternately through a special program connecting the MQ5CF with IQ009 interface on the mini-usb PROG port on the back side.

[WHP001 - Firmware update procedure](#)

Documento generato automaticamente da **Qem Wiki** - <https://wiki.qem.it/>

Il contenuto wiki è costantemente aggiornato dal team di sviluppo, è quindi possibile che la versione online contenga informazioni più recenti di questo documento.