

## **Inhaltsverzeichnis**





The electrical features are given in paragraph **Electrical features**.  
The wiring examples are given in paragraph **Connection examples**

CN28	Terminal	Symbol	Description	Address
	1	GAI	Common for analog inputs	
	2	IA1	analog input 1	3.AI01
	3	SEL1V	Analog input selector 1 voltmetric 0-10V <sup>1)</sup>	
	4	SEL1C	Analog input selector 1 amperometric 0-20mA <sup>2)</sup>	
	5	GAI	Common for analog inputs	
	6	IA2	analog input 2	3.AI02
	7	SEL2V	Analog input selector 2 voltmetric 0-10V <sup>3)</sup>	
	8	SEL2C	Analog input selector 2 amperometric 0-20mA <sup>4)</sup>	
	9	VREF	Reference voltage	

<sup>1), 3)</sup> Connecting this terminal to GAI, the input functions as voltmetric 0-10V

<sup>2), 4)</sup> Connecting this terminal to GAI, the input functions as amperometric 0-20mA

CN29	Terminal	Symbol	Description	Address
	1	GAI	Common for analog inputs	
	2	IA3	analog input 3	3.AI03
	3	SEL3V	Analog input selector 3 voltmetric 0-10V <sup>1)</sup>	
	4	SEL3C	Analog input selector 3 amperometric 0-20mA <sup>2)</sup>	
	5	GAI	Common for analog inputs	
	6	IA4	analog input 4	3.AI04
	7	SEL4V	Analog input selector 4 voltmetric 0-10V <sup>3)</sup>	
	8	SEL4C	Analog input selector 4 amperometric 0-20mA <sup>4)</sup>	
	9	VREF	Reference voltage	

<sup>1), 3)</sup> Connecting this terminal to GAI, the input functions as voltmetric 0-10V

<sup>2), 4)</sup> Connecting this terminal to GAI, the input functions as amperometric 0-20mA

Documento generato automaticamente da **Qem Wiki** - <https://wiki.qem.it/>

Il contenuto wiki è costantemente aggiornato dal team di sviluppo, è quindi possibile che la versione online contenga informazioni più recenti di questo documento.