

Sommario



The electrical features are given in paragraph [Electrical features](#).
The wiring examples are given in paragraph [Connection examples](#)

CN13	Terminal	Symbol	Description	Address
	1A	VD1	n.c.	
	2A	DIR1+	DIRECTION output 1	3.PULSE01
	3A	STEP1+	STEP output 1	
	4A	DIR2+	DIRECTION output 2	
	5A	STEP2+	STEP output 2	
	6A	0V	Common for stepper outputs	
	1B	VD1	n.c.	
	2B	DIR1-	Complementary DIRECTION output 1	Complementary outputs for use in drives with Line-Driver inputs
	3B	STEP1-	Complementary output STEP 1	
	4B	DIR2-	Complementary output DIRECTION 2	
	5B	STEP2-	Complementary output STEP 2	
	6B	0V	Common for stepper outputs	
CN14	Terminal	Symbol	Description	Address
	1A	VD1	n.c.	
	2A	DIR1+	DIRECTION output 3	3.PULSE03
	3A	STEP1+	STEP output 3	
	4A	DIR2+	DIRECTION output 4	
	5A	STEP2+	STEP output 4	
	6A	0V	Common for stepper outputs	
	1B	VD1	n.c.	
	2B	DIR1-	Complementary output DIRECTION 3	Complementary outputs for use in drives with Line-Driver inputs
	3B	STEP1-	Uscita complementare STEP 3	
	4B	DIR2-	Complementary output DIRECTION 4	
	5B	STEP2-	Complementary output STEP 4	
	6B	0V	Common for stepper outputs	

Documento generato automaticamente da **Qem Wiki** - <https://wiki.qem.it/>

Il contenuto wiki è costantemente aggiornato dal team di sviluppo, è quindi possibile che la versione online contenga informazioni più recenti di questo documento.