

Sommario

2 analog inputs, 12bit potentiometric, voltmetric and amperometric

The electrical features are given in paragraph [Electrical features](#).
The wiring examples are given in paragraph [Connection examples](#)

CN17	Terminal	Symbol	Description	Address
	1	GAI	Common for analog inputs	
	2	IA1	Analog input 1	3.AI01
	3	SEL1V	Analog input 1 selector, voltmetric 0-10V ¹⁾	
	4	SEL1C	Analog input 1 selector, amperometric 0-20mA ²⁾	
	5	GAI	Common for analog inputs	
	6	IA2	Analog input 2	3.AI02
	7	SEL2V	Analog input 2 selector, 0-10V voltmetrico ³⁾	
	8	SEL2C	Analog input 2 selector, 0-20mA amperometric ⁴⁾	
	9	VREF	Reference voltage	

^{1), 3)} Wiring this terminal to GAI, the input functions as 0-10V voltmetric

^{2), 4)} Wiring this terminal to GAI, the input functions as 0-20mA amperometric

Documento generato automaticamente da **Qem Wiki** - <https://wiki.qem.it/>

Il contenuto wiki è costantemente aggiornato dal team di sviluppo, è quindi possibile che la versione online contenga informazioni più recenti di questo documento.