

**Sommario**



**AN030 - Application update procedure with MMC for J1-P11 and J1-K31** ..... 3

*Premise* ..... 4

*Procedure* ..... 4



**AN030 - Application update procedure with MMC for J1-P11 and J1-K31**

			
<b>Document:</b>	<b>AN030</b>		
<b>Description:</b>	Application update procedure with MMC for J1-P11 and J1-K31		
<b>Editor:</b>	Riccardo Furlato		
<b>Approver</b>	Gabriele Bazzi		
<b>Link:</b>	<a href="http://www.qem.eu/doku/doku.php/appnote/an030">http://www.qem.eu/doku/doku.php/appnote/an030</a>		
<b>Language:</b>	English		
Document Release	Description	Note	Date
01	New manual		27/01/2016


## Premise


Before switching to the application update from MMC there are some premises to be respected:


- The MMC must be formatted with a filesystem type FAT12, FAT16 or FAT32;
- Before copying the files to the MMC, it is recommended that you format it.
- The file must be named as: appqtp.bin


## Procedure



1. Turn off the instrument.
2. Insert the MMC/SD as shown on the screen in the picture (the MMC remains protruding).






3. Press and hold the **F1**  button to access the **SYSTEM FUNCTIONS**.
4. Turn on the instrument.


5. Press the **F1**  button until the following screen appears



6. Press the **BOOT**  button or **ENTER**  button for 2 seconds to execute the selected function.
7. The following screen appears to indicate that the operation is in progress



8. A successful operation pops up the message SUCCESSFUL to indicate that the operation is successful.
9. If the function fails, the  **POW** LED will be switched off and starts flashing the  **ERR** LED.



N.B.: In this case, repeat the procedure carefully from the beginning and if necessary, contact the Assistance.

10. Press the **F1**  button to restart the system.

Documento generato automaticamente da **Qem Wiki** - <http://wiki.qem.it/>

Il contenuto wiki è costantemente aggiornato dal team di sviluppo, è quindi possibile che la versione online contenga informazioni più recenti di questo documento.